

DALI 2-8V 6.4W multicurrent dimmable driver (650-800mA)


Ref. PE10DA09

DALI dimmable multi-current driver 6.4W. Regulation with DALI protocol. Constant current output, for LED fixtures of 2-8V and current intensity between 650mA and 800mA. The driver incorporates an EMC filter, does not produce flicker (NO FLICKER), and regulates the lighting smoothly and consistently without jumps and without noise. Settable multi-current via DIP Switch. 650ma, 700ma, 750ma, and 800ma.



Product data

Certs	CE, ROHS
Dimensions (mm) LxWxH	135x43.5x26.5
Power factor (cosφ)	0.95
Frequency (Hz)	50
Frequency of Use	Intensive
Guarantee	According to legal warranty: 3 years
IP	IP20
Maximum power (W)	6.4
Temperature range	-20~+65°F
Sensor	No
Control system	DALI
Output Voltage (V)	2-8V-DC
Nominal Voltage (V)	200-240V-AC
Outdoor Use	No
Service life (h)	25,000





Product variants

Reference Attributes



PE10DA09