



Power supply 24V DC 6W 0.25A 100-240V

Ref. B1565-6W

Constant voltage transformer driver to 24V-DC with a power of 6W. Versatile, dust-proof, short circuit resistant, over-voltage, over-power, over-current, and over-temperature protection functions. Widely used in 24V-DC LED strips or 24V DC electronic devices. Power supply designed exclusively for indoor use, with constant output voltage. The electronic protection circuit of the power supply disconnects in case of short circuit or overload in the secondary circuit, overheating. After the faults are resolved, the LED power supply automatically resets to resume operation. Input 100-240V and a constant voltage output of 24V-DC 0.25A.

Product data

| | |
|-----------------------|--------------------------------------|
| Certs | CE, ROHS |
| Dimensions (mm) LxWxH | 55x40x20mm |
| Power factor (cosφ) | 0.6 |
| Frequency (Hz) | 50 - 60 |
| Frequency of Use | normal |
| Guarantee | According to legal warranty: 3 years |
| Maximum intensity (A) | 0.25 |
| IP | IP20 |
| Material | Plastic |

| | |
|---------------------|---------------|
| Power (W) | 6 |
| Temperature range | -20°F ~ +40°F |
| Output Voltage (V) | 24V |
| Nominal Voltage (V) | 100 - 240V AC |
| Outdoor Use | No |
| Service life (h) | 25,000 |

Product variants

Reference

Attributes

B1565-6W

